

PRODUCT SHEET - POWER SUPPLY FROM MILLETEKNIK

Product image



Name, article number and e-number

Name	Item number	E-number (sv)
Voltage Converter 24V-12V 2A	A-VC002402A01LM01	52 135 92

Designation

Optional card for voltage conversion from 24 V to 12 V.

Area of use

The product converts 24 V to 12 V.

Technical description

The card provides 2 A continuously, 3 A in peak (short-term). 10 V - 60 V.

Outputs

Three load outputs, two of which are controllable.

Alarm

Sum-alarm in the event of an earth fault.

Fuses

Outputs is current limited, which is why additional load protection is not needed.

Indications and communication

LED on card lights up when incoming supply is connected and output is connected.

Weight

Name	Net weight	Weight incl. packaging
Voltage converter 24V-12V 2A	0.2 kg	1 kg

Installation requirements

The product must be installed in a compatible product from Milleteknik.

The accessories fits in

Product series	Enclosure size	Number of cards that can fit ^a
ECO	M	2
ECO, NEO, NOVA	FLX S	2
EN54, NEO, NOVA	FLX M	3
NEO, NOVA	FLX L	3
19 rack module holders	4U	8

^aThe number of cards/accessories that can fit is the total number that can fit in the housing. Electronic and mechanical limitations may exist.

Requirements that the product meets

EMC:	EMC Directive 2014 / 30EU
Electricity:	Low voltage directive: 2014/35 / EU
CE:	CE directive according to: 765/2008
Environment	REACH Regulation: Directive 1907/2006, WEEE Regulation: Directive 20021961E, RoHS Regulation: Directive 2015/863



Guarantee

The product has a two-year warranty against manufacturing defects. Batteries and wearing parts are not covered by warranty.

Manufacturing, lifespan, environmental impact and recycling

Manufactured by Milleteknik in Partille, Sweden.

The product is designed for a long service life, which reduces the environmental impact. End-of-life products are handed over to the nearest recycling centre.

Link to the latest information

Products and software are subject to updates, you will always find the latest information on our website.

Accessories & options

About this information

All information is published subject to possible errors. This document is updated without notice.