

## PRODUCT SHEET - POWER SUPPLY FROM MILLETEKNIK

### Product image



### Name, article number and e-number

Name	Item number	E-number (sv)
Voltage Converter 24V-12V 6A	A-VC002406A01LM01	52 135 93

### Designation

Optional card for voltage conversion from 24 V to 12 V.

### Area of use

The product converts 24 V to 12 V.

### Technical description

The card provides 6 A continuously, 10 A in peak (short-term). 10 V - 60 V.

### Outputs

A controllable load output.

### Alarm

Alarm functions are missing.

### Fuses

Output is current limited, which is why additional load protection is not needed.

### Indications and communication

LED on card lights up when incoming supply is connected and output is connected.

### Weight

Name	Net weight	Weight incl. packaging
Voltage converter 24V-12V 6A	0.2 kg	1 kg

### Installation requirements

The product must be installed in a compatible product from Milleteknik.

### The accessories fits in

Product series	Enclosure size	Number of cards that can fit <sup>a</sup>
ECO	M	2
ECO, NEO, NOVA	FLX S	2
EN54, NEO, NOVA	FLX M	3
NEO, NOVA	FLX L	3
19 rack module holders	4U	8

<sup>a</sup>The number of cards/accessories that can fit is the total number that can fit in the housing. Electronic and mechanical limitations may exist.

### Requirements that the product meets

EMC:	EMC Directive 2014 / 30EU
Electricity:	Low voltage directive: 2014/35 / EU
CE:	CE directive according to: 765/2008
Environment	REACH Regulation: Directive 1907/2006, WEEE Regulation: Directive 20021961E, RoHS Regulation: Directive 2015/863



### Guarantee

The product has a two-year warranty against manufacturing defects. Batteries and wearing parts are not covered by warranty.

### Manufacturing, lifespan, environmental impact and recycling

Manufactured by Milleteknik in Partille, Sweden.

The product is designed for a long service life, which reduces the environmental impact. End-of-life products are handed over to the nearest recycling centre.

### Link to the latest information

Products and software are subject to updates, you will always find the latest information on our website.

### Accessories & options

### About this information

All information is published subject to possible errors. This document is updated without notice.